PPG1000C

1000 kVA

ROUNDED CATALOGUE CLASS

Cummins diesel generator | Open set

Designed and manufactured in the United Kingdom

ENGINE PLATFORM

Cummins

KTA38G3

Model-specific drawing supplied with quotation.

Configuration and appearance are confirmed with the quotation.

SELECTED CONFIGURATION

ENGINE

Cummins KTA38G3

ALTERNATOR

Stamford S6L1D-D41

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

PRIME POWER / PRP

931 kVA 745 kW

STANDBY POWER / ESP

1010 kVA 808 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	1000	800	910	728
400	SS	1010	808	931	745

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.

Perkins Power Generators is a trading name of GenPro Power Solutions.
Exact build, performance and delivery scope are confirmed in the quotation.

Technical specification

PPG1000C | Cummins **KTA38G3** | Open set

ENGINE

Manufacturer	Cummins
Model	**KTA38G3**
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	12
Arrangement	At Vee
Displacement	37.8L
Bore	159mm
Stroke	159mm
Compression ratio	13.9:1
Cooling	Liquid Cooled
Coolant capacity	210L
Oil capacity	140L

ALTERNATOR

Manufacturer	Stamford
Model	**S6L1D-D41**
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	**MX321**
Voltage regulation	0.5%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD	75% LOAD	100% LOAD	110% LOAD
104 L/h	**151 L/h**	**198 L/h**	**221 L/h**

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

Dimensions, weight, fuel tank and model-specific drawing are confirmed with the quotation.

No complete matching frame data is published for this selected configuration.

OTHER CONFIGURATIONS IN THIS CATALOGUE CLASS

Engine	Alternator	V / phase	ESP kVA	PRP kVA
QST30G4	Stamford **S6L1D-D41**	400 / 3	1010	940

Engineering data above apply only to the selected configuration on page 1.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.
PPG technical specification | Reviewed 2026-10-12

Perkins Power Generators is a trading name of GenPro Power Solutions.
Exact build, performance and delivery scope are confirmed in the quotation.