PPG1000PS

1000 kVA
ROUNDED CATALOGUE CLASS

Perkins diesel generator | Acoustic canopied

Designed and manufactured in the United Kingdom

ENGINE PLATFORM

Perkins

4008TAG1A

Model-specific drawing supplied with quotation.

SELECTED CONFIGURATION

ENGINE
Perkins 4008TAG1A

ALTERNATOR
Stamford S6L1D-D41

ELECTRICAL OUTPUT
400 V | 3-phase | 50 Hz

Configuration and appearance are confirmed with the quotation.

PRIME POWER / PRP
911 kVA 729 kW

STANDBY POWER / ESP
1000 kVA 800 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	999	799	910	728
400	SS	1000	800	911	729

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.

Perkins Power Generators is a trading name of GenPro Power Solutions.
Exact build, performance and delivery scope are confirmed in the quotation.

Technical specification

PPG1000PS | Perkins **4008TAG1A** | Acoustic canopied

ENGINE

Manufacturer	Perkins
Model	**4008TAG1A**
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	8
Arrangement	In Line
Displacement	30.561L
Bore	160mm
Stroke	190mm
Compression ratio	13.6:1
Cooling	Liquid Cooled
Coolant capacity	149L
Oil capacity	153L

ALTERNATOR

Manufacturer	Stamford
Model	**S6L1D-D41**
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	**MX321**
Voltage regulation	0.5%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD	75% LOAD	100% LOAD	110% LOAD
98 L/h	**143 L/h**	**195 L/h**	**218 L/h**

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

Dimensions, weight, fuel tank and model-specific drawing are confirmed with the quotation.

No complete matching frame data is published for this selected configuration.

OTHER CONFIGURATIONS IN THIS CATALOGUE CLASS

Engine	Alternator	V / phase	ESP kVA	PRP kVA
4008TAG1A	Leroy Somer **TAL049D**	400 / 3	1004	910

Engineering data above apply only to the selected configuration on page 1.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.
PPG technical specification | Reviewed 2026-10-12

Perkins Power Generators is a trading name of GenPro Power Solutions.
Exact build, performance and delivery scope are confirmed in the quotation.